





Project:	
Location:	
Cat.No:	
Type:	
Lamps:	Qty:
Notes:	

## Example: CH2AA600S001X

CH2		600					
Series	Voltage Config. Input/Output	Unit Size	Battery Time	Nol	Qty Ckt Breakers	Qty Nol Ckt Breakers	Options
CH2 - Chloride Synthesis ( UPS System Emergency Lighting Application	AA - 120/120 DH2 JJ - 277/277 I for JA - 277/120	600 - 600 VA	S - 90 min X - 10 min Y - 20 min	0 - No 1 - Yes w/ TDT	01X - 1 OCB* 02X - 2 OCB 03X - 3 OCB 04X - 4 OCB 12X - 12 OCB 01A - 1 OCBA 02A - 2 OCBA 03A - 3 OCBA 06A - 6 OCBA (maximum 12 pole spaces)	A - 1 B - 2 C - 3 D - 4 E - 5 F - 6 G - 7 H - 8 I - 9 J - 10 K - 11 L - 12 Z - None	FSU – Start-Up Service EXT- Extended Warranty <sup>1</sup>
<sup>2</sup> Optimum oper	y available with FSU. ating temperature of batterie lbove 85°F (30°C) adversely in				* 1 OCB is standard, substitute corresponding designator for optional configurations.		

### unit check list

Catalog No:					
VA Rating: 600					
Battery Type: Sealed Lead Calcium					
Operating Time: 90/20/10 Min.					
Utility Input:VAC, Single Phase					
Output Circuit Breakers:		Normally	Normally	Trip Aları	~
Qty:AC Volts:	Amps:	ON _	Normally OFF	YES	NO 🗌
Qty:AC Volts:	Amps:	ON	OFF	YES 🗌	NO 🗌
Qty:AC Volts:	Amps:	ON	OFF	YES 🗌	NO 🗌
Qty:AC Volts:	Amps:	ON	OFF	YES 🗌	NO $\square$
Options: FSU EXT					
Remarks:					



## CH2 Synthesis Single Phase Uniterruptible Power Supply

### 600 VA

#### codes and standards

UL 924 listed

#### construction

- Free standing, NEMA 1 enclosure with lockable control access panel.
- · Double conversion, no interruption.
- · Solid state pulse width modulated inverter.
- · Internal inverter bypass switch.
- Standard, UL 924 compliant, 90 minute battery back up.
- UL 924 auxiliary equipment 10 and 20 minute back up available.
- · Microprocessor control and diagnostic system.
- · LED array system status panel
- · Fault annunciating audible alarm.
- · Current limiting start sequence.
- Single output circuit breaker is standard, additional circuit breakers (OCB) or circuit breakers with trip alarms (OCBA) can be added.
- Optional normally off load (NOL) energizes only during power outage, is user programmable from 0-15 minutes.
- · Seismic anchoring compatible.
- Operating temperature range 32°F (0°C) to 104°F (40°C)2.
- · Audible noise less than 50 dB at 3 ft on "A" weighted scale.
- · Automatic low battery voltage disconnect.

#### application

- The solid state pulse width modulated (PWM) inverter offers enhanced load compatibility.
- It operates incandescent, magnetic and electronic ballast fluorescent, high power factor compact fluorescent and high intensity discharge (HID) luminaries.
- Provides conditioned, uninterruptible power for other types of critical loads.
- Consult factory for non-lighting load applications.

#### electronics - input

- Input power factor correcting to 0.97.
- Frequency range 60 Hz, ±2.5 Hz.
- · Input harmonic current distortion < 5% THD.
- IEEE 587 ANSI C 62.41-1980 surge suppression.

#### electronics - output

- · Sine wave output.
- Voltage regulation ±2%.
- Frequency regulation synchronized to utility, free running 60 Hz, ±0.5%.
- · Output voltage distortion maximum 3% THD with linear load.
- · Load power factor capability 0.7 lead to 0.7 lag.
- Overload capability 150% for 1 minute with utility power source present.

#### warranty

- Standard warranty: electronics warranty is 12 months from date of shipment. Battery warranty is 1 year full, 9 years prorata from date of shipment.
- Extended warranty available: consult factory for extended warranty and service option.

# CH2 Synthesis Single Phase Uniterruptible Power Supply

600 VA

## system input/output

System Rating	600 VA
Input Voltage (V) : Input Current	120 : 11.7
	277 : 5.5
Output Voltage (V) : Output Current	120 : 5.0
	277 : 2.16
OCB Pole Spaces Available	
Without Trip Alarm	12
With Trip Alarm	6
Heat Rejection (btu/hr)	546
Weights (lbs)	
120 V with 90 min battery	269
277 V with 90 min battery	303

#### dimensions





