

RC159Z Safety Cable

911401809187



Accessory, Gray

Philips CoreLine panel Gen6 delivers on the CoreLine promise of innovation, easy installation, and excellent illumination. Designed as a direct replacement for functional luminaires in general lighting applications, this LED panel light’s innovative All-in feature offers a choice of three lumen packages and three-color temperatures in a single luminaire. This makes it easy to select the right product, gives you the flexibility respond to customer preferences on site, and means fewer product codes on stock. Installing the CoreLine RC132V LED panel is quick and easy, using the product’s quick connector or flywire. The CoreLine range includes Interact Ready luminaires with integrated wireless communications, ready to be used with Interact gateways, sensors, and software.

General Information

Value ladder	Performance
--------------	-------------

Mechanical and Housing

Overall length	1,500 mm
Overall width	20 mm
Overall height	3.7 mm
Overall diameter	1.5 mm

Dimensions (Height x Width x Depth)	4 x 20 x 1500 mm
Material	Steel
Ingress protection code	-
Mech. impact protection code	-
Accessory color	Gray
Net Weight (Piece)	0.020 kg

Approval and Application

CE mark	Yes
EU RoHS compliant	Yes


Sustainability Data

Non-virgin material ratio of the packaging	Cardboard > 80% recycled
Packaging Recyclable content ratio	Cardboard recycling rate > 80%
Packaging Material	Cardboard

Product Data

Order product name	RC159Z Safety Cable
Full product name	RC159Z Safety Cable
Full product code	872016975247499
Order code	911401809187
Material Nr. (12NC)	911401809187
Numerator - Quantity Per Pack	1
EAN/UPC - Product/Case	8720169752474
Numerator - Packs per outer box	40
EAN/UPC - Case	8720169752528

Dimensional drawing



Related Documents

Documents and certificates	Document Name	Download
Tender text	Tender_Text_911401809187_en_EG.txt	Download
Installation Instructions	RC159Z-Safety-Cable-Installation-instruction.pdf	Download
Installation Instructions	CoreLine-panel-G6-Installation-Instructions-RC132V-BN.pdf	Download

