



The **CWE Series** is a wet location exit sign, featuring a polycarbonate housing and waterproof design suitable for wet location. The CWE series can be wall, ceiling or end mounted.

Project: \_\_\_\_\_  
 Location: \_\_\_\_\_  
 Cat.No: \_\_\_\_\_  
 Type: \_\_\_\_\_  
 Lamps: \_\_\_\_\_ Qty: \_\_\_\_\_  
 Notes: \_\_\_\_\_

## Ordering guide

Family	Power	Letter Color	Housing	Faces
<b>CWE</b> Wet Location Exit	<b>A</b> AC only <b>N</b> NiCad battery	<b>R</b> Red <b>G</b> Green	<b>W</b> White <b>B</b> Black	<b>U-1</b> Single/Double faceplate

## Accessories

**T20TPTOOL** Tamper-proof screws and screwdriver kit

## Specifications

### Codes and standards

- UL listed to standard 924
- NFPA 101 (Life Safety Code)
- UL listed for wet locations (0° C – 50° C)
- Meets CEC title 20 regulations

### Power Consumption

- AC version: 120/277 VAC dual voltage input, 2W, 25mA
- Battery version: 2.2W, 25mA

### Construction

- Housing constructed of 5VA flame retardant, UV stabilized polycarbonate
- High impact resistant, UV stabilized polycarbonate clear lens
- Corrosion resistant enclosure with engineering grade silicone gasket

### Mounting

- Suitable for wall mount, ceiling mount and side mount
- Universal knock-out pattern on back plate for wall mount

### Battery

- Maintenance-free, 3.6V rechargeable NiCd (NiCad) battery
- Provides a minimum of 90 minutes of emergency power and takes 24 hours to recharge
- Must be recharged at least once in 9 months

### Electronics

- LED indicator light alerts occupant on battery condition (Green-normal, Red-check battery)
- Internal solid-state transfer switch automatically connects the internal battery to LED board for minimum 90-minute emergency illumination
- Battery-powered models include brownout detection, AC lockout, low voltage disconnect, AC power indicator and push-to-test switch
- Battery-powered models support self-diagnostic feature to ensure reliable operation and compliance with electrical and life-safety codes. Tests are executed monthly for 1 minute and annually for 90 minutes

### Warranty

- Five-year limited warranty on all electronics and housing, battery prorated for 2 years
- Battery must be recharged at least once in 9 months

